

Data Sheet

VIAVI SmartOTDR Handheld Fiber Tester

The affordable, easy-to-use handheld tester for techs at any level

The lightweight and compact SmartOTDR speeds and optimizes field testing of metro and access networks— with a tailored OTDR interface and automatic analysis that any technician can understand.

With SmartOTDR, generic or user-defined setup configurations eliminate setup errors and maintain results consistency. One-touch operation and a single results window ensure fast and easy measurements, while robust wireless connectivity options increase productivity anywhere.



Benefits

- Combines all essential fiber tests in one handheld with visual fault locator (VFL), optical power meter (OPM), and P5000i microscope options
- Simplifies OTDR analysis with Smart Link Mapper (SLM) result view
- Upgrades easily in the field
- Automates testing with objective, pass/fail results
- Enhances productivity anywhere with powerful network connectivity options)

Features

- Single-/dual-/tri-wavelength versions with 1310/1550 nm and in-service 1625 or 1650 nm wavelengths
- Light, compact, hands-free design includes 5" high-visibility outdoor touch screen
- Integrated CW light source
- PON optimized to test through 1x128 splitter ratio with FTTH-SLM
- Built-in broadband and dual-band selective power meter (1490/1550/1577 nm)
- Automated fiber inspection and macrobend detection with pass/fail analysis software
- 3G/4G connectivity via USB, Bluetooth[®]/ WiFi options
- 3-year warranty*
- All-day battery life

*Except 100AS version

Powerful Connectivity


Several connectivity options (3G/4G smartphones via USB and optional Bluetooth/WiFi) enable remote control as well as data and work-order transfers toand-from tablets, smartphones, and computers. The SmartOTDR quickly resolves field issues in real time, and optional SmartAccess Anywhere (SAA) can open a tunnel in the cloud so a technician can remotely access and operate the instrument. Compatible with a wide range of cloud servers (WebDAV service providers), the SmartOTDR can also instantly share measurement reports using onboard FastReport .pdf report generation.

SmartOTDR includes a one-year trial of cloud-based StrataSync[™] for asset, configuration, and test-data management, and to ensure that all instruments have the latest software and options installed.



Post-processing Remote coaching

Connectivity features and options enhance workflows







- 1. 5-inch high-visibility capacitive touch screen
- 2. Charge indicator
- 3. On indicator
- 4. File menu
- 5. Setup menu
- 6. Start/Stop
- 7. Testing indicator
- 8. On/Off
- 9. Home page
- 10. Cancel (switch off functions)

- 11. Direction and validation keys
- 12. Results page
- 13. Loudspeaker
- 14. AC/DC input
- 15. Slave mini USB port
- 16. Visual fault locator (VFL)
- 17. Master USB ports
- 18. OTDR port/continuous light source/power meter
- 19. OTDR live port (in-service test)/dual-band power meter
- 20. WiFi/Bluetooth options

Specifications (typical at 25°C)

General									
Display	5-inch capacitive color touc	5-inch capacitive color touch screen (12.5 cm)							
Display resolution	800 x 480 W VGA								
Interfaces	2x USB 2.0 ports, 1x mini-USB 2.0 port, built-in Bluetooth and WiFi (optional, dongles also available)								
Storage	10,000 OTDR traces typical								
Battery	Rechargeable Lithium-polymer battery, up to 20 hours of operation ¹								
Power supply	AC/DC adapter, input 100-250 V AC, 50-60 Hz; 2.5 A max, output 12 V DC, 25 W								
Electrical safety	EN60950 compliant								
Size (HxWxD)	175 x 138 x 57 mm (6.9 x 5.4 x 2.24 in)								
Weight (battery included)	Approx. 0.9 kg (1.98 lb)								
Operating/storage temperature	Operating: –20 to +50°C; storage: –20 to +60°C								
Humidity (noncondensing)	95%								
OTDR									
Laser safety class (21 CFR)	Class 1								
Number of data points	Up to 256,000 data points								
Display range	0.1 km to 260 km								
Sampling resolution	4 cm								
Distance accuracy	$(\pm 1 \text{ m}) \pm (\text{sampling resolution}) \pm (1.10^{-5} \text{ x distance})$, excluding group index uncertainties								
Attenuation resolution	0.001 dB								
Attenuation linearity	±0.04 dB/dB								
	SmartOTDR 100AS	SmartOTDR 100A	SmartOTDR 100B						
Central wavelength ²	1310/1550 nm ±20 nm	1310/1550/1650 nm ±20 nm	1310/1550/1625/1650 nm ±20 nm						
RMS dynamic range ³	30/30 dB	37/35/32 dB	40/40/41/41 dB						
Pulse widths	5 ns to 20 µs	5 ns to 20 µs	3 ns to 20 µs						
Event dead zone⁴	1.35 m	1.35 m	0.9 m						
Attenuation dead zone⁵	4 m	4 m	2.5 m						
Splitter attenuation dead zone	Not available	Not available	45 m after 15 dB splitter loss						
CW Light Source [®]									
Output power level ⁶	–3.5 dBm								
Stability long term (8 hr) ⁷	±0.05 dB								
Built-in Broadband Power Meter	r (optional)								
Operating mode	270, 330, 1 kHz, 2 kHz, and T	270, 330, 1 kHz, 2 kHz, and TWINTest							
Power level range	0 to -55 dBm								
Calibrated wavelengths	1310, 1490, 1550, 1625, and 1650 nm								
Measurement accuracy ⁸	±0.5 dB	±0.5 dB							
Built-in Visual Fault Locator (opt	ional)								
Wavelength	650 nm	650 nm							
Emission mode	CW, 1 Hz								
Laser class	Class 2 per EN60825-1 and FDA21 CFR Part 1040.10 standards								
Built-in Dual-band Power Meter	(E118FA65PPM version)								
Wavelengths	1310/1550 nm; 1490/1550 nm; 1490/1577 nm								
Measurement ranges	1310/1490 nm: –35 to +5 dB	1310/1490 nm: –35 to +5 dBm; 1550/1577 nm: –35 to +23 dBm							
Measurement accuracy	±0.5 dB								

1. Per Telcordia GR-196-CORE.

2. Laser at 25°C and measured at 10 $\mu s.$

3. The one-way difference between the extrapolated backscattering level at the start of the fiber and the RMS (SNR=1) noise level, after 3 minutes of averaging using the largest pulsewidth.

4. Measured at ±1.5 dB below the peak of an unsaturated reflective event using the shortest pulse width.

5. Measured at ± 0.5 dB from the linear regression using a FC/UPC-type reflectance and the shortest pulse width.

6. ±1 dB.

7. After light source stabilization, warm-up time of 20 min.

8. At calibrated wavelengths and at -30 dBm.

9. Not available on filtered wavelengths

Ordering Information

SmartOTDR Configurations	Part Number		
All configurations include a hands-free soft case with neck strap, a stylus for capacitive touch scree and SC/PC or SC/APC connector(s).	en, a Lithium-Polymer battery		
SmartOTDR 1550 nm AS-range handheld tester	E100AS-PC/-APC*		
SmartOTDR 1550 nm A-range handheld tester	E100A-APC*		
SmartOTDR filtered 1650 nm A-range handheld tester	E118FA65-APC*		
SmartOTDR filtered 1650 nm A-range handheld tester with broadband and dual-band in-line selective power meter	E118FA65PPM-APC*		
SmartOTDR 1310/1550 nm A-range handheld tester	E126A-PC/-APC*		
SmartOTDR 1310/1550/filtered 1650 nm A-range handheld tester	E138FA65-PC/-APC*		
SmartOTDR 1310/1550 nm B-range handheld tester	E126B-APC*		
SmartOTDR 1310/1550/filtered 1625 nm B-range handheld tester	E136FB-APC*		
SmartOTDR 1310/1550/filtered 1650 nm B-range handheld tester	E138FB65-APC*		
Additional OTDR Connector Adapters	· ·		
5C universal adapter	EUSCADS/EUSCADS-APC		
EC universal adapter	EUFCADS		
.C universal adapter	EULCADS/EULCADS-APC		
Accessories			
Additional AC Adapter/Charger	E20PWMC		
Additional Lithium Polymer battery	E10LIPO		
Additional hands-free soft case with neck strap	E10GLOVE		
Additional stylus for capacitive touch screen	EHVT-STYLUS		
arge soft carrying case (optional)	E40SCASE1		
12 V car lighter adapter (optional)	E40LIGHTER		
EU/US-to-India type D power adapter (optional)	EINDIADPLUG		
JSB GPS receiver	EUSBGPSRECEIVER		
Dptional Tools			
/FL with 2.5 mm UPP adapter	E10VFL		
Optical power meter option (same port as OTDR)	E10PM		
25000i digital microscope kit with 7 tips	ESDFSCOPE5KI		
Built-in WiFi/Bluetooth (BLE)	E10WIFIBLUE		
External WiFi USB dongle/Bluetooth (BLE)	EWIFIBLUE		
Software Options			
FTTH-SLM Base - Tailored OTDR App. for FTTH Networks (Basic PON Architectures)	ESMARTFTTH-100-BASE		
TTH-SLM Premium - Tailored OTDR App. for FTTH Networks (Advanced PON Architectures, including Jnbalanced/tapered Splitters)	ESMARTFTTH-100		
TTH-SLM Assistant - Simplified Set-up Mode for FTTH-SLM Base or FTTH-SLM Premium Apps	EFTTHSLM-ASSIST-100		
-TTA-SLM - Tailored OTDR App. for FTTA Networks	ESMARTFTTA-100		
nterprise-SLM - Tailored OTDR App. for Enterprise and Datacenter Networks	ENTERPRISE-100		
ABLE-SLM - Management and Automation of High Count Fiber Cables OTDR Measurements	ESMARTCABL-100		
martAccess Anywhere - Remote Access and Control from Anywhere	SAA-100-L2		
GPS - Embedded GPS Coordinates into Test Files and Reports	EGPS		
Additional Software Options			
Addition of 1310 nm wavelength (E100A and E100AS versions only)	E113-UPG		
SmartLink Mapper/SLM view (E100AS version only)	ESMARTLINK100UP		
Increased Dynamic Range - 37/35 dB at 1310/1550 nm (E100AS version only)	EXTRANGE100UP		

* For ordering in the USA replace E for F in the part number, e.g. E100AS-PC becomes F100AS-PC

VIAVI Care Support Plans

Increase your productivity for up to 5 years with optional VIAVI Care Support Plans:

- Maximize your time with on-demand training, priority technical application support and rapid service.
- Maintain your equipment for peak performance at a low, predictable cost.

Plan availability depends on product and region. Not all plans are available for each product or in every region. To find out which VIAVI Care Support Plan options are available for this product in your region, contact your local representative or visit: <u>viavisolutions.com/viavicareplan</u>

Features

reatures									*5-year plans only
Plan	Objective	Technical Assistance	Factory Repair	Priority Service	Self-paced Training	5 Year Battery and Bag Coverage	Factory Calibration	Accessory Coverage	Express Loaner
BronzeCare	Technician Efficiency	Premium	\checkmark	\checkmark	\checkmark				
SilverCare	Maintenance & Measurement Accuracy	Premium	\checkmark	\checkmark	\checkmark	\checkmark^{\star}	\checkmark		
MaxCare	High Availability	Premium	\checkmark	\checkmark	\checkmark	\checkmark^{\star}	\checkmark	\checkmark	\checkmark



Contact Us +1 844 GO VIAVI (+1 844 468 4284)

To reach the VIAVI office nearest you, visit viavisolutions.com/contact

© 2021 VIAVI Solutions Inc. Product specifications and descriptions in this document are subject to change without notice. Patented as described at viavisolutions.com/patents smartotdr-ds-fop-nse-ae 30176148 905 0521

viavisolutions.com